

Transistor Type No.	N/P G/S	Manufacturer	Lead Ident.	Out-line	Maximum (V)			Maximum Power		Max. T. ^o C	Frequency Resp.(MHz)	Leakage		Gain	
					V _{ca}	V _{ce} '	V _{ES}	I _c	Power			I _{co} @ V _{ca}	V _{ca}	h _{FE}	@ I _c
2N3193	P S	STC	731	TO 53	80	80	10.0	5.000A	85.000W	200J	HF AMP	1MA	80V	16	3.000A
2N3194	P S	STC	731	TO 53	100	100	10.0	5.000A	85.000W	200J	HF AMP	1MA	100V	16	3.000A
2N3195	P S	STC	605	TO 3	40	40	10.0	5.000A	75.000W	200J	HF AMP	1MA	40V	16	3.000A
2N3196	P S	STC	605	TO 3	60	60	10.0	5.000A	75.000W	200J	HF AMP	1MA	60V	16	3.000A
2N3197	P S	STC	605	TO 3	80	80	10.0	5.000A	75.000W	200J	HF AMP	1MA	80V	16	3.000A
2N3198	P S	STC	605	TO 3	100	100	10.0	5.000A	75.000W	200J	HF AMP	1MA	100V	16	3.000A
2N3217	P S	RAY SPR	211	TO 46	15	10	15.0	.100A	.400W	200J	1.000G	1NA	15V	60	.001A
2N3218	P S	RAY SPR	211	TO 46	25	20	25.0	.100A	.400W	200J	1.000G	1NA	25V	60	.001A
2N3219	P S	RAY SPR	211	TO 46	40	35	40.0	.100A	.400W	200J	1.000G	1NA	40V	40	.001A
2N3226	N S	BEN FTC	605	TO 3	35	35		5.000A	75.000W	200J	.020E	2MA	35V	32	2.000A
2N3227	N S	MOT	210	TO 18	40	20	6.0	.500A	.360W	200J	500.000G	200NA	20V	180	.010A
2N3229	N S	RCA	540	TO 60	105	60	4.0	2.500A	17.500W	200J	200.000G	100NA	30V		
2N3232	N S	STC BEN WHE	605	TO 3	60	60	6.0	7.500A	117.000W	200J	HF AMP	5MA	80V	38	
2N3233	N S	STC WHE	605	TO 3	100	100	6.0	7.500A	117.000W	200J	HF AMP	5MA	110V	38	
2N3234	N S	STC WHE	605	TO 3	160	160	6.0	7.500A	117.000W	200J	HF AMP	5MA	160V	38	
2N3235	N S	STC BEN WHE	605	TO 3	55	55	7.0	15.000A	117.000W	200J	HF AMP	5MA	65V	46	
2N3236	N S	STC WHE	605	TO 3	100	90	7.0	15.000A	150.000W	200J	HF AMP	5MA	90V	40	
2N3237	N S	STC WHE	605	TO 3	90	75	7.0	20.000A	200.000W	200J	HF AMP	5MA	75V	24	
2N3238	N S	STC WHE	605	TO 3	80	80	8.0	15.000A	150.000W	200J	HF AMP	5MA	80V	16	
2N3239	N S	STC WHE	605	TO 3	80	80	8.0	15.000A	150.000W	200J	HF AMP	5MA	80V	16	
2N3240	N S	STC WHE	605	TO 3	160	160R	8.0	15.000A	150.000W	200A	HF AMP	5MA	160V	16	
2N3241A	N S	RCA	211	TO104	30	25	7.5	.500W	.360W	175J	175.000G	100NA	25V	150	.010A
2N3242A	N S	RCA	211	TO104	40	40	8.0	.500W	.360W	175J	175.000G	10NA	25V	200	.010A
2N3244	P S	RAY MOT TII	211	TO 5	40	40	5.0	1.000A	.360W	200J	175.000G	50NA	30V	90	.500A
2N3245	P S	RAY MOT TII	211	TO 5	50	50	5.0	1.000A	.360W	200J	150.000G	50NA	50V	50	.500A
2N3248	P S	MOT	210	TO 18	15	12	5.0	.360W	.360W	200J	250.000G	50NA	10V	80	.010A
2N3249	P S	MOT	210	TO 18	15	12	5.0	.360W	.360W	200J	300.000G	50NA	10V	180	.010A
2N3250	P S	MOT RAY FSC TII	211	TO 18	50	40	5.0	.200A	.360W	200J	250.000G	20NA	40V	90	.010A
2N3250A	P S	MOT RAY TII	211	TO 18	60	60	5.0	.200A	.360W	200J	250.000G	20NA	40V	90	.010A
2N3251	P S	MOT RAY FSC TII	211	TO 18	50	40	5.0	.200A	.360W	200J	300.000G	20NA	40V	200	.010A
2N3251A	P S	MOT RAY TII	211	TO 18	60	60	5.0	.200A	.360W	200J	300.000G	20NA	40V	200	.010A
2N3252	N S	FSC TII RAY MOT ITT AMP	211	TO 5	60	30	5.0	1.000A	1.000W	200J	200.000G	500NA	40V	50	.500A
2N3253	N S	FSC TII RAY MOT ITT AMP	211	TO 5	75	40	5.0	1.000A	1.000W	200J	175.000G	500NA	60V	40	.375A
2N3254	N S	FSC MOT	211	TO 5	80	50	5.0	1.000A	1.000W	200J	150.000G	500NA	60V	32	.500A
2N3261	N S	RCA	211	TO 52	40	15	6.0	.500A	.300W	175J	300.000G	25NA	15V	50	.100A
2N3262	N S	RCA	211	TO 39	100	80	4.0	1.500A	1.000W	175J	150.000G	100NA	30V	80	.500A
2N3263	N S	RCA	913	913A	150	90	7.0	25.000A	84.000W	200J	20.000G	4MA	80V	44	15.000A
2N3264	N S	RCA	913	913A	120	60	7.0	25.000A	84.000W	200J	20.000G	10MA	60V	40	15.000A
2N3265	N S	RCA	561	TO 63	150	90	7.0	25.000A	125.000W	200J	20.000G	4MA	80V	44	15.000A
2N3266	N S	RCA	561	TO 63	120	60	7.0	25.000A	125.000W	200J	20.000G	10MA	60V	40	15.000A
2N3268	N S	TRW	210	TO 5	45	45	1.0		2.500W		12.500G	500NA	30V	32	.010A
2N3279	P G	MOT	217	TO 72	30	20	1.0	.050A	.100W	100J	400.000G	5UA	10V	30	.003A
2N3280	P G	MOT	217	TO 72	30	20	1.0	.050A	.100W	100J	400.000G	5UA	10V	30	.003A