

Transistor Type No.	N, P, S	Manufacturer	Lead Ident.	Out-line	Maximum (V)			Maximum		Max. T. (°C)	Frequency Resp. (MHz)	Leakage		Gain	
					V _{CB}	V _{CE}	V _{EB}	I _C	Power			I _{CO}	V _{CB}	I _C	h _{FE}
2N1487	N S	AMF REN RCA TII ETC	605	TU 3	60	40	10.0	6.000A	75.000W	200J	1.000B	25UA	30V	30	1.500A
2N1488	N S	AMF BEN TII ETC	605	TO 3	100	55	10.0	6.000A	75.000W	200J	1.000B	25UA	30V	30	1.500A
2N1489	N S	AMF BEN RCA TII ETC	605	TO 3	60	40	10.0	6.000A	75.000W	200J	1.000B	25UA	30V	40	1.500A
2N1490	N S	AMF REN RCA TII ETC	605	TO 3	100	55	10.0	6.000A	75.000W	200J	1.000B	25UA	30V	40	1.500A
2N1491	N S	RCA	217	TO 12	30		1.0	.005A	.500W	175C	250.000B	10UA	12V	60	
2N1492	N S	RCA	217	TO 12	60		2.0	.005A	.500W	175C	275.000B	10UA	12V	60	
2N1493	N S	RCA	217	TO 12	100		4.5	.005A	.500W	175C	300.000B	10UA	12V	0	
2N1494	P G	MOT	211	211P	20	15	4.0	.500A	.750W	100J	110.000G	7UA	5V	35	.400A
2N1494A	P G	MOT	211	211P	20	15	4.0	.500A	.750W	100J	110.000G	7UA	5V	50	.200A
2N1495	P G	MOT	210	TO 5	40	25	4.0	.500A	.300W	100J	150.000G	7UA	5V	50	.200A
2N1496	P G	MOT	211	211P	40	25	4.0	.500A	.750W	100J	150.000G	7UA	5V	50	.200A
2N1499	P G	ETC	170	TO 9	20	15S	2.0	.050A	.025W	85J		100UA	20V	30	.040A
2N1499A	P G	SPR ETC	170	TO 9	20	20S	2.0	.100A	.060W	100J	100.000G	3UA	5V	50	.040A
2N1499B	P G	SPR ETC	170	TO 9	30	20	2.0	.100A	.075W	100J	150.000G	3UA	5V	80	.010A
2N1500	P G	SPR ETC	170	TO 9	15	12S	2.0	.050A	.060W	100J	120.000G	5UA	5V	50	
2N1501	P G	SOL	427	TO 10	60	40	28.0	3.500A	32.000W	100J	.200G	2MA	60V	60	2.000A
2N1502	P G	SOL	427	TO 10	40	40	28.0	3.500A	32.000W	100J	.200G	2MA	40V	60	2.000A
2N1505	N S	TRW	210	TO 5	50	40R	3.0	.500A	.800W	175J	70.000G	50UA	28V	50	
2N1506	N S	BEN TRW	210	TO 5	60	40R	4.0	.500A	.800W	175J	140.000G	50UA	28V	50	
2N1506A	N S	BEN TRW	210	TO 5	80	50	5.0	.500A	.800W	200J	140.000G	50NA	28V	50	
2N1507	N S	TRW TII RAY ETC	211	TO 5	60	25	5.0	.500A	.600W	175J	50.000G	1UA	30V	160	
2N1510	-N G	GEC	12	12A	75	70R	8.0	.020A	.075W	85J		5UA	75V	50	
2N1511	N S	STC	405	TO 36	60	40	10.0	6.000A	75.000W	200A	1.000B	25UA	30V	30	
2N1512	N S	STC	405	TO 36	100	55	10.0	6.000A	75.000W	200A	1.000B	25UA	30V	30	
2N1513	N S	STC	405	TO 36	60	40	10.0	6.000A	75.000W	200A	1.000B	25UA	30V	50	
2N1514	N S	STC	405	TO 36	100	55	10.0	6.000A	75.000W	200A	1.000B	25UA	30V	50	
2N1518	P G	DEL ETC	405	TO 36	50	40	30.0	25.000A	150.000W	100J	.004E	4MA	50V	30	15.000A
2N1519	P G	DEL ETC	405	TO 36	80	60	30.0	25.000A	150.000W	100J	.004E	4MA	80V	30	15.000A
2N1520	P G	DEL ETC	405	TO 36	50	40	30.0	35.000A	150.000W	100J	.004E	4MA	50V	34	15.000A
2N1521	P G	DEL ETC	405	TO 36	80	60	30.0	35.000A	150.000W	100J	.004E	4MA	80V	34	15.000A
2N1522	P G	DEL ETC	405	TO 36	50	40	30.0	50.000A	150.000W	100J	.004E	4MA	50V	50	15.000A
2N1523	P G	DEL ETC	405	TO 36	80	60	30.0	50.000A	150.000W	100J	.004E	4MA	80V	50	15.000A
2N1524	P G	RCA	120	TO 1	24		.5	.010A	.080W	71A	33.000B	16UA	12V	60	
2N1525	-P G	RCA	55	TO 40	24		.5	.010A	.080W	71A	33.000B	16UA	12V	60	
2N1526	P G	RCA	120	TO 1	24		.5	.010A	.080W	71A	33.000B	16UA	12V	130	
2N1527	-P G	RCA	55	TO 40	24		.5	.010A	.080W	71A	33.000B	16UA	12V	130	
2N1529	P G	BEN MOT ETC	605	TO 3	40	20	20.0	5.000A	90.000W	100J	.010E	2MA	25V	30	3.000A
2N1529A	P G	MOT REN	605	TO 3	40	20	20.0	5.000A	106.000W	110J	.004E	2MA	25V	30	3.000A
2N1530	P G	BEN MOT ETC	605	TO 3	60	30	30.0	5.000A	90.000W	100J	.010E	2MA	40V	30	3.000A
2N1530A	P G	MOT REN	605	TO 3	60	30	30.0	5.000A	106.000W	110J	.004E	2MA	40V	30	3.000A
2N1531	P G	BEN MOT ETC	605	TO 3	80	40	40.0	5.000A	90.000W	100J	.010E	2MA	55V	30	3.000A
2N1531A	P G	MOT REN	605	TO 3	80	40	40.0	5.000A	106.000W	110J	.004E	2MA	55V	30	3.000A
2N1532	P G	BEN MOT ETC	605	TO 3	100	50	50.0	5.000A	90.000W	100J	.010E	2MA	65V	30	3.000A